# Your mobile.....

Confirm an option (press the middle of the key)

Pick up Send a call

I.I Keys

In idle screen:

Access call log (Redial) (press)

Switch on/Switch off the telephone (press and hold) End call

Return to idle screen

Left softkey

Access your voicemail (press and hold)

- Press: access the symbols table - Press and hold: enter zero

- Press: change input methods

#\_ In idle screen:

- Press: # - Press and hold: activate/deactivate vibrate mode In Edit mode:

- Press: - (space)

From Idle screen - Press: dial '5'

- Press and hold: switch the LED Flashlight on/off



6 LED Flashlight

Navigation key:

Profiles A

Calendar •

Menu/Confirm an option

PROTECT YOUR HEARING

To prevent possible hearing damage, do not listen at high volume levels for long periods. Exercise caution when holding your device near your ear while the loudspeaker

**Ouick Start Guide** 

For more information about how to use the phone, please go

to www.alcatelonetouch.com to download complete user

manual (English version only). Moreover, from the website

you can also consult FAQ, realize software upgrade, etc.

**ALCATEL** 







# Call log .....

(English version only).

You can access the function using the following options:

- Select R from main menu Press the send key from Home screen
- For dual SIM model, the complete contacts of both SIMI and SIM2 are available in this menu (1).

#### 6.2 Available options

When you press "Options", you can have access to View, Send SMS. Save to Contacts, Edit before call. Add to blacklist, Add to whitelist, Delete etc.



(I) 1041D only.

English - CIB27F602AAA

# Camera .....

Your mobile phone is fitted with a camera for taking photos that you can use in different ways:

- Store them in your "My files\Images"
- Customise your main screen.

Make sure that microSD card is well inserted before taking

Left softkey

Call log

Right softkey

End call

Voicemail

Pick up/Send call

(press and hold)

Switch on/Switch off

# Settings ..... 10

From the main menu, select the menu icon and select the function of your choice in order to customise your telephone: Profiles, Phone settings, Call settings, Network, Connectivity, Security, Regulatory & Safety, Restore

# Tools.....

Your mobile phone has a built-in alarm clock with a snooze

## 9.2 Calculator

Enter a number, select the type of operation to be performed, and enter the second number, then press "=" to display the

## 9.3 Calendar

Once you enter this menu from the main menu, there is a monthly-view calendar for you to query date.

#### 9.4 Notes

Notes" from the main menu.

Access this feature by pressing to enter the main menu, then selecting "Tools\Bluetooth"

#### 9.6 Converter

Weight converter and Length converter.

## 9.7 Voice Alarm

With this menu, you may create the voice file and set it as the

#### 9.8 Fake call

This program enables you to call yourself by simulating a caller number/name, ringtone at a scheduled time. It helps you to politely escape from social situations at any time you wish. This call can be rejected by  $\stackrel{ ext{ wo}}{ ext{ wo}}$  key.

#### 9.9 Call filter

Enable blacklist, all callers in the list will be automatically blocked. Enable whitelist, only callers in the list can be connected. You are allowed to add 20 contacts to each list from the Contacts, call log, Messages or create directly by pressing .

You can create a note in text format by accessing "Tools\ To light in darkness, you may activate "Torch" by below

## Rhijetooth

9.11 WAF

Access Wap options: Homepage, Bookmarks, Go to URL, Recent pages, Settings.

nurnoses only

9.10 Torch

Make sure that MicroSD card is well inserted before accessing this feature.

In idle screen, press and hold 75 to activate the flashlight;

press or press and hold 55 to deactivate it.

(1) The icons and illustrations in this guide are provided for information

#### 9.12 Services

Contact your network operator to check service availability.

# Media.....

that particular area.

Your phone is equipped with a radio (1) with RDS functionality. You can use the application as a traditional radio with saved channels or with parallel visual information related to the radio program on the display if you tune to stations that offer Visual Radio service. You can listen to it while running other applications.

The quality of the radio depends on the coverage of the radio station in

# Getting started......

## Removing and installing the back cover



## Removing and installing the battery















Place the SIM card with the chip facing downwards and slide it into its housing. Make sure that it is correctly inserted. To remove the card, press it and slide it out.

## 10.2 Images

A library links to the images (stored in "My images") in phone or SD card to multi-mark, set as wallpaper, power on/off display or sent by Bluetooth, etc.

## 10.3 Recorder

Accessing "Recorder" allows you to make voice or sound





## Charging the battery



Connect the battery charger to your phone and mains socket

- Charging may take about 20 minutes to start if the battery is
- Be careful not to force the plug into the socket. Make sure the battery is correctly inserted before connecting
- the charger. The mains socket must be near to the phone and easily accessible (avoid electric extension cables).
- When using your telephone for the first time, charge the battery fully (approximately 3 hours). You are advised to fully charge the battery ( ).
- battery is fully charged, disconnect your charger from the plug; reduce the backlight time, etc.



Hold down the \_\_\_\_ key until the phone powers on.

## 2.3 Power off your phone

2.2 Power on your phone

Hold down the week from the main screen.

# Calls .....

## 3.1 Making a call

call. If you make a mistake, you can delete the incorrect digits by

To hang up the call, press the \_\_\_\_ key.

#### Making an emergency call

pressing the right softkey.

If your phone is covered by the network, dial emergency number and press the \_\_ key to make an emergency call. This works even without a SIM card and without typing the PIN code.

## 3.2 Calling your voicemail (

To access your voicemail, hold down the weekey.

## 3.3 Receiving a call

To reduce power consumption and energy waste, when When you receive an incoming call, press the Ley to talk and then hang up using the \_\_\_\_ key.

## 3.4 Available functions during the call

During a call, you can use your directory, your calendar, short messages, etc. without losing your correspondent

Contacts.....

## 4.1 Consulting your contacts

Dial the desired number then press the Level to place the To access the Contacts from the main screen, press the key and select the 🔲 icon from the menu.

## 4.2 Adding a contact

You can add a new contact to phone or SIM card by selecting "Add contact"





## 5.1 Create message


From the main menu select "Messages" to create text. You can type a message and you can also modify a predefined message in Templates. While writing a message, select "Options" to access all of the messaging options. You can save your messages that you send often to **Drafts**.



Specific letters (accent) will increase the size of the SMS, this may cause multiple SMS to be sent to your recipient.

Contact your network operator to check service availability

You will have access to all audio and visual files stored in memory To write messages, there are two writing methods card in My files. You can access a number of items with this · Normal: this mode allows you to type a text by choosing a





letter or a sequence of characters associated with a key.

writing of your text.

Press and hold: enter zero

Latin input mode ....

Predictive with the eZi mode (1): this mode speeds up the

+ key in edit mode Press: access the symbols table

> ALCATEL is a trademark of Alcatel-Lucent and used under license by TCT Mobile Limited.

All rights reserved © Copyright 2013 TCT Mobile Limited.

TCT Mobile Limited reserves the right to alter material or technical specification without prior notice

## PROTECT YOUR HEARING

To prevent possible hearing damage, do not listen at high volume levels for long periods. Exercise caution when holding your device near your ear while the loudspeaker is in use.

2014-1-3 18:16:32

IP4751\_ALCATEL 1041X\_1041D\_QG\_Eng\_GB\_Sri lanka\_02\_140103.indd 1



vibrate with the exception of the alarm SMS unread Flight mod

I.2 Main screen icons (1)

Battery charge level

Call forwarding activated: your calls are forwarded

Silence mode: your phone does not ring, beep or

Alarm or appointments programmed

Level of network reception

Voicemail message received

Inserting and removing the SIM card











## option: My audios, Images, Received, etc.

To release the microSD card holder, slide it in the direction of the arrow and lift it. Then insert the microSD card with the golden contact downward. Finally, turn down the microSD holder and slide it in the opposite direction to lock it.







(I) 1041X only.



Given that studies show that using a mobile phone while driving a ehicle constitutes a real risk, even when the hands-free kit is used (car kit, headset...), drivers are requested to refrain from using their mobile

When driving do not use your phone and headphone to listen to music or to the radio. Using a headphone can be dangerous and forbidden in

interfere with the vehicle's electronic systems such as ABS anti-lock brakes or airbags. To ensure that there is no problem:

- do not place your phone on top of the dashboard or within an airbag deployment area.
- check with your car dealer or the car manufacturer to make sure that the dashboard is adequately shielded from mobile phone RF energy. CONDITIONS OF LISE

You are advised to switch off the telephone from time to time to optimise its performance.

Switch the phone off before boarding an aircraft.

Switch the phone off when you are in health care facilities, except in designated areas. As with many other types of equipment now in electronic devices, or equipment using radio frequency.

Switch the phone off when you are near gas or flammable liquids. Strictly obey all signs and instructions posted in a fuel depot petrol station or chemical plant, or in any potentially explosive atmosphere.

When the phone is switched on it should be kept at least 15 cm from any medical device such as a pacemaker, a hearing aid or insulin pump etc. In particular when using the phone, you should hold it against the ear on the opposite side to the device, if any,

To avoid hearing impairment, pick up the call before holding your phone to your ear. Also move the handset away from your ear while using the "hands-free" mode because the amplified volume might cause

Do not let children use the phone and/or play with the telephone and accessories without supervision. When replacing the cover please note that your phone may contain

substances that could create an allergic reaction Always handle your phone with care and keep it in a clean and dust-

Do not allow your phone to be exposed to adverse weather or environmental conditions (moisture, humidity, rain, infiltration of liquids, dust, sea air, etc). The manufacturer's recommended operating temperature range is -10°C to +55°C.

·LICENCES

Obigo® is a registered trademark of Obigo AB.

microSD Logo is a trademark.

eZiText™ and Zi™ are trademarks of Zi Zicorporation Corporation and/or its Affiliates.



The Bluetooth word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by TCT Mobile Limited and its affiliates is under license. Other trademarks and trade names are those of their respective owners.

ALCATEL 1041X/1041D Bluetooth **QD ID B021548** 

IP4751 ALCATEL 1041X 1041D QG Eng GB Sri lanka 02 140103.indd 2

At over 55°C the legibility of the phone's display may be impaired. though this is temporary and not serious

ou should never rely only on your phone for emergency calls.

Do not drop, throw or bend your mobile phone. Do not use the phone if the glass made screen, is damaged, cracked or

Use only batteries, battery chargers, and accessories which are nended by TCT Mobile Limited and its affiliates and are compatible

liability for damage caused by the use of other chargers or batteries. important information stored in your phone

history of such occurrences, please consult your doctor before playing video games on your phone or enabling a flashing-lights feature on your

please take the following safety precautions:

- Take a minimum of a 15-minute break hourly.
- Play at the farthest distance possible from the screen
- If your hands, wrists, or arms become tired or sore while playing, stop
- playing, stop the game and see a doctor.

When you play games on your phone, you may experience occasional discomfort in your hands arms shoulders neck or other parts of your body. Follow the instructions to avoid problems such as tendinitis, carpal



#### PROTECT YOUR HEARING To prevent possible hearing damage, do not listen at high

volume levels for long periods. Exercise caution when holding your device near your ear while the loudspeaker is in use.

# Telephone warranty ......

Your phone is warranted against any defect or malfunctioning which may occur in conditions of normal use during the warranty period of twelve (12) months (1) from the date of

six (6) months (1) from the date of purchase as shown on your An electronic version of this user guide is available in English and other

> In case of any defect of your phone which prevents you from normal use thereof, you must immediately inform your vendor and present your phone with your proof of purchase.

same defect. Repair or replacement may be carried out using reconditioned components offering equivalent functionality.

This warranty covers the cost of parts and labor but excludes

The warranty period may vary depending on your country.

The life of a rechargeable mobile phone battery in terms of conversation

different applicable electrical specifications, a charger you purchased in one for a Class B digital device pursuant to part 15 of the FCC Rules. These urisdiction may not work in another jurisdiction. They should be used for

RADIO WAVES Specific Absorption Rate (IFFF)

THIS MOBILE PHONE MEETS THE GOVERNMENT'S REQUIREMENTS FOR EXPOSURE TO RADIO WAVES.

Your mobile phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits for exposure to radiorequency (RF) energy. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific regarizations through periodic and thorough evaluation of scientific studies ese guidelines include a substantial safety margin designed to ensure the safety of all persons, regardless of age and health

he exposure standard for mobile phones employs a unit of measurement nown as the Specific Absorption Rate, or SAR.

The SAR limit set by public authorities such as the sion of the US Government (FCC), or h Industry Canada, is 1.6 W/kg averaged over 1 gram of body tissue. Tests for SAR are conducted using standard operating positions with the mobile phone transmitting at its highest certified power level in all tested

Although the SAR is determined at the highest certified power level, the actual SAR level of the mobile phone while operating can be well below the maximum value. This is because the mobile phone is designed to operate at multiple power levels so as to use only the power required reach the network. In general, the closer you are to a wireless base

Before a mobile phone model is available for sale to the public, compliance with national regulations and standards must be shown. The highest SAR value for this model mobile phone when tested is

W/kg for use at the ear and 1.51 W/kg for use close to the body. While there may be differences between the SAR levels of various mobile phones and at various positions, they all meet the government requirement or RF exposure. For body-worn operation, the mobile phone meets FCC RF exposure guidelines provided that it is used with a non-metallic accessory with the handset at least 1.0 cm from the hody. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. Additional information on SAR can be found on the Cellular ecommunications & Internet Association (CTIA) Web site: http:// www.

The World Health Organization (WHO) considers that present scientific information does not indicate the need for any special precautions for use of mobile phones. If individuals are concerned, they might choose to limit eir own or their children's RF exposure by limiting the length of calls, or using "hands-free" devices to keep mobile phones away from the head and Additional WHO information about electromagnetic fields and public health

are available on the following website: http://www.who.int/peh-emf. Note: This equipment has been tested and found to comply with the limits

This warranty shall not apply to defects to your phone and/or accessory due to (without any limitation):

Non-compliance with the instructions for use or installation, or with technical and safety standards applicable in the geographical area where your phone is used,

2) Connection to any equipment not supplied or not recommended by TCT Mobile Limited.

Modification or repair performed by individuals not authorised

Modification, adjustment or alteration of software or hardware performed by individuals not authorized by TCT Mobile Limited

5) Inclement weather, lightning, fire, humidity, infiltration of liquids or foods, chemical phones, download of files, crash, high voltage, corrosion, oxidation...

Your phone will not be repaired in case labels or serial numbers (IMEI) have been removed or altered.

implied, other than this printed limited warranty or the mandatory warranty provided by your country or jurisdiction.

extent those damages can be disclaimed by law.

Some countries/states do not allow the exclusion or limitation of indirect, incidental or consequential damages, or limitation of the duration of implied warranties, so the preceding limitations or exclusions may not apply to you.

Tests for SAR are conducted using standard operating positions with limits are designed to provide reasonable protection against harmful the device transmitting at its highest certified power level in all tested interference in a residential installation. This equipment generates use and can radiate radio frequency energy and, if not installed and used in accordance with the instructions may cause harmful interference to radio ALCATEL INALY: unications. However, there is no guarantee that interference to radio or television recention, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the

interference by one or more of the following measures: Reorient or relocate the receiving antenna. Increase the senaration between the equipment and receiver

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/ TV technician for help. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. For the receiver devices associated with the operation of a licensed radio

service (e.g. FM broadcast), they bear the following statement: This device complies with Part 15 of the FCC Rules. Operation is subject to the condition that this device does not cause harmful interference. For other devices, they bear the following sta

This device complies with Part 15 of the FCC Rules. Operation is subject

(1) this device may not cause harmful interference his device must accept any interference received, including interference

that may cause undesired operation Your mobile phone is equipped with a built-in antenna. For optimal operation, you should avoid touching it or degrading it.

As mobile devices offer a range of functions, they can be used in posi

other than against your ear. In such circumstances the device will be compliant with the guidelines when used with headset or USB data cable. If you are using another accessory ensure that whatever product is used is free of any metal and that it positions the mobile phone at least 1.0 cm

Specific Absorption Rate (ICNIRP)

Proof of compliance with internal ional standards (ICNIRP) or with European Directive 1999/5/EC (R&TTE) is required of all mobile phone models before they can be put on the market. The protection of the health and safety for the user and any other person is an essential ent of these standards or this directive IIS DEVICE MEETS INTERNATIONAL GUIDELINES FOR EXPOSURE

TO RADIO WAVES our mobile device is a radio transmitter and receiver. It is designed not to exceed the limits for exposure to radio waves (radio frequence

guidelines were developed by an independent scientific organization ICNIRP) and include a substantial safety margin designed to assure the safety of all persons, regardless of age and health.

The radio wave exposure guidelines use a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit for mobile devices

## My phone cannot charge properly

Before contacting the service centre, you are advised to follow the instructions below:

You are advised to fully charge ( ) the battery for optimal

Avoid storing large amounts of data in your phone as this may affect its performance.

Use User Data Format (1) to perform phone formatting (to perform User Data format, hold down # key while simultaneously pressing the power on/off key under power off mode). ALL User phone data: contacts, messages and files will be lost permanently. It is strongly advised to fully backup the phone data and profile before doing formatting.

#### My phone cannot switch on

Check the battery contacts, remove and reinstall your battery,

If it still does not work, please use User Data Format (1) to reset the phone

# My phone is frozen or has not responded for several

#### My phone turns off by itself

Make sure power off key is not mis-contacted

- reset the phone

frequency bands. The highest SAR values under the ICNIRP guidelines for

#### Maximum SAR for this model and conditions under which it was recorded Hoad SAR GSM 900 + Bluetooth 0.748 W/kg Body-worn SAR GSM 900 + Bluetooth 1.00 W/kg

#### ALCATEL IMID

Maximum SAR for this model and conditions under which it was recorded.		
Head SAR	GSM 900 + Bluetooth	0.748 W/kg
Body-worn SAR	GSM 900 + Bluetooth	1.00 W/kg

During use, the actual SAR values for this device are usually well below

the values stated above. This is because, for purposes of system efficiency and to minimize interference on the network, the operating power of your mobile device is automatically decreased when full power is no eded for the call. The lower the power output of the device, the lower ite SAR value Body-worn SAR testing has been carried out at a separation distance of

10 mm. To meet RF exposure guidelines during body-worn operation, the device should be positioned at least this distance away from the body. If you are not using an approved accessory ensure that whatever produc is used is free of any metal and that it positions the phone the indicated distance away from the body. Organizations such as the World Health Organization and the US Food

and Drug Administration have stated that if people are concerned and ant to reduce their exposure they could use a hands-free device to keep the phone away from the head and body during phone calls, or reduce the amount of time spent on the phone. For more information you can go to www.alcatelonetouch.com

Additional information about electromagnetic fields and public health are available on the following site: http://www.who.int/peh-emf. Your telephone is equipped with a built-in antenna. For optimal operation you should avoid touching it or degrading it

As mobile devices offer a range of functions, they can be used in positions other than against your ear. In such circumstances the device will be compliant with the guidelines when used with headset or ush data cable If you are using another accessory ensure that whatever product is used is free of any metal and that it positions the phone at least 10 mm away from the hody

### Regulatory information

The following approvals and notices apply in specific regions as noted.

dentification du produit : ALCATEL 1041X type Tiger L EU 1SIM VGA

Tab (procedum enquerments with respect to excitating text compatibility (7 visus 3.1.3.) emoss de protection en ce qui concerne las compatibilités électromagnétique)

- EN 301 489-1 v.1.9.2 (2011-09), EN 301 489-7 v.1.3.1 (2005-11), EN 301 489-17 v.2.1.

EN 55013-2001 +4.12-2003 + 2.22-2005. EN 55002-2007-4.11-2011

s ( protection of the nessin and or the salety of the user sécurilé de l'utilisateur) EN 80550.1-2008 + 511-2009 + 51-2010 + 512-2011

directive 2011/65/EU (RoHS - restriction of the u

EN301 489-34 v1.1.1 (2010-10) EN301 489-34 v1.3.1 (2012-05) EN 82884-2010

TCTMobile

C€1588

# dentification / Identification du produit : ALCATEL 1041D type Tiger L EU 2SIM VGA dgenoes de protection en ce qui concerne la compatibilité électromagnitique ) -- En 301 489-1 v.1.9.2 (2011-09), EN 301 489-7 v.1.3.1 (2005-11), EN 301 489-17 v.2. S. EN 550132001 +A120031 +A22006, EN 550202007+A112011 s product can connect with a Common Mobile Phone Charger which compiles with below standard - EN301 489-34 v1.1.1 (2010-10) - EN301 489-34 v1.3.1 (2012-05)

TCTMobile

TCT Mobile Europe SAS - Siège social : 55 Avenue des Champs Pierreux, Immeuble Le Capitole 92000 Nanterre Fr SAS au capital de 21,021,027 augres - PCS Mantere B 440,008,222 - Sivel 440,008,222,000,38,40F 44507

## Unable to receive incoming calls

CT Mobile Europe SAS - Siège social : 55 Avenue des Champs Pierreux, immeuble Le Capitole 92000 Nanterro F GAS -- anchal de 23 031 072 auros - RCS Nanterre B 440 038 222 - Stet 440 038 222 000 38 APE 46022

· Make sure your phone is switched on and connected to a network (check for overloaded or unavailable network)

Check your subscription status with your operator (credit, SIM card valid, etc.)

Make sure you have not forwarded incoming calls

Make sure that you have not barred certain calls Make sure that your phone is not in flight mode

minutes to display the battery charger indicator on the screen The caller's name/number does not appear when a call is received · Check that you have subscribed to this service with your

When abroad, check that the voltage input is compatible operator

Your caller has concealed his/her name or number

# I cannot find my contacts

· Make sure your SIM card is not broken Make sure your SIM card is inserted properly

Import all contacts stored in SIM card to phone

#### The sound quality of the calls is poor Try connecting at a later time if the network is overloaded

 You can adjust the volume during a call by pressing the 
 he Check the network strength

#### Make sure that the receiver, connector or speaker on your phone is clean

# I am unable to use the features described in the manual

#### Check with your operator to make sure that your subscription includes this service

 Make sure this feature does not require an ALCATEL ONE TOUCH accessory

## When I select a number from my contacts, the number cannot be dialed

· Make sure that you have correctly recorded the number in

• Make sure that you have inputted the country prefix when calling a foreign country

and files will be lost permanently. Please store phone data in SIM card before you want to format

I am unable to add a contact in my contacts · Make sure that your SIM card contacts are not full; delete some files from your SIM card or save the files in the phone

My callers are unable to leave messages on my voicemail

Contact your network operator to check service availability

#### I cannot access my voicemail

· Make sure your operator's voicemail number is correctly entered in "Messages\Voicemai"

Try later if the network is busy

The flickering icon is displayed on my standby screen You have saved too many short messages on your SIM card:

### delete some of them or archive them in the phone memory SIM card PIN locked

 Contact your network operator to obtain the PUK code (Personal Unblocking Key)

## How to make your battery last longer

Make sure you follow the complete charge time (minimum

After a partial charge, the battery level indicator may not be exact. Wait for at least 20 minutes after removing the charger to obtain an exact indication

Switch on the backlight upon request

Contact your network operator to check service availability.

ergency call numbers may not be reachable on all cellular networks.

Do not open, dismantle or attempt to repair your mobile phone yourse

broken to avoid any injury. Do not paint it.

with your phone model. TCT Mobile Limited and its affiliates disclaim any Remember to make back-up copies or keep a written record of all

Some people may suffer epileptic seizures or blackouts when exposed to flashing lights, or when playing video games. These seizures or blackouts may occur even if a person never had a previous seizure or blackout. If you have experienced seizures or blackouts, or if you have a family

Parents should monitor their children's use of video games or other features that incorporate flashing lights on the phones. All persons should discontinue use and consult a doctor if any of the following symptoms occur: convulsion, eye or muscle twitching, loss of awareness, involuntary rements, or disorientation. To limit the likelihood of such symptoms.

- Do not play or use a flashing-lights feature if you are tired or need sleep.
- Play in a room in which all lights are on
- and rest for several hours before playing again. f you continue to have sore hands, wrists, or arms during or afte

tunnel syndrome, or other musculoskeletal disorders.

# **General information......**

Internet address: www.alcatelonetouch.com Hot Line Number: see "TCT Mobile Services" leaflet or go to our

Road, Tsimshatsui, Kowloon, Hong Kong On our Internet site, you will find our FAQ (Frequently Asked Questions) section. You can also contact us by e-mail to ask any

languages according to availability on our server: www.alcatelonetouch.com Your telephone is a transceiver that operates on GSM networks with

900 and 1800 MHz bands.

tions you may have.

This equipment is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. The entire copy of the Declaration of Conformity for your telephone can be obtained through our website; www.alcatelonetouch.com.

Your telephone is identified by an IMEI (phone serial number) shown on the packaging label and in the phone's memory. We recommend that you note the number the first time you use your telephone by entering \* # 0 6 # and keep it in a safe place. It may be requested by the police or your operator if your telephone is stolen. This number allows your

mobile telephone to be blocked preventing a third person from using it

Protection against theft (1)

## even with a different SIM card **Disclaimer**

There may be certain differences between the user manual description and the phone's operation, depending on the software release of your

TCT Mobile shall not be held legally responsible for such differences, if any, nor for their potential consequences, which responsibility shall be borne by the operator exclusively.

Address: Room 1910-12A, Tower 3, China HK City, 33 Canton

purchase as shown on your original invoice. Batteries (2) and accessories sold with your phone are also warranted against any defect which may occur during the first

se note that you must respect the laws and regulations in force in

jurisdiction or other jurisdiction(s) where you will use your mobile

one regarding taking photographs and recording sounds with your

idden to take photographs and/or to record the voices of other

em, as this may be considered to be an invasion of privacy. It is the

iser's sole responsibility to ensure that prior authorisation be obtained.

a photograph of another person; the manufacturer, the seller or vendor o

Before removing the battery from your phone, please make sure that the

Do not attempt to open the battery (due to the risk of toxic fumes and

Do not burn or dispose of a used battery in household rubbish or store

Batteries must be disposed of in accordance with locally applicable

environmental regulations. Only use the pattery for the purpose for which it was designed. Never use damaged batteries or those not recommended

hey will then be recycled, preventing substances being disposed of in the

s of equipment with this symbol are not to be thrown into ordinary

ties; instead they are to be taken to collection points for them to be

pins if your jurisdiction or your region has suitable recycling and collection

CALITION: DICK OF EVELOCIONI IE BATTERY IS DEDITACED BY AN

INCORRECT TYPE, DISPOSE OF USED BATTERIES ACCORDING TO

Mains powered chargers will operate within the temperature range of: 0

The chargers designed for your mobile phone meet with the standard for

safety of information technology equipment and office equipment use

They are also compliant to the ecodesign directive 2009/125/EC. Due to

This symbol on your telephone, the battery and the accessories

means that these phones must be taken to collection points at

Municipal waste disposal centres with specific hins for these

ions. Only use the battery for the purpose for which

Do not puncture, disassemble or cause a short-circuit in a battery

It from the improper use of the mobile phone

Observe the following precautions for battery use:

it at temperatures above 60 °C

European Union countries

THE INSTRUCTIONS

In non European Union jurisdictions:

TCT Mobile Limited and/or its affiliates

the end of their life:

items of equipment

- Collection hins at points of sale

hese collection points are accessible free of charge

nment so that their components can be reused

All phones with this sign must be brought to these collection points.

BATTERY.

If the defect is confirmed, your phone or part thereof will be either replaced or repaired, as appropriate. Repaired Phone and accessories are entitled to a one (I) month warranty for the

time standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optima performance for your phone during the first six months after purchase and for approximately 200 more recharges.

by TCT Mobile Limited or its affiliates or your vendor.

There are no express warranties, whether written, oral or

In no event shall TCT Mobile Limited or any of its affiliates be liable for indirect, incidental or consequential damages of any nature whatsoever, including but not limited commercial or financial loss or damage, loss of data or loss of image to the full

Troubleshooting.....

then turn your phone on Check the battery power level, charge for at least 20 minutes

Restart your phone by pressing and holding the 
 — key

 If it still does not work, please use User Data Format (1) to reset the phone

• If it still does not work, please use User Data Format (1) to

Make sure you are using an ALCATEL ONE TOUCH battery

and the charger from the box Clean the battery contact if it's dirty Make sure your battery is inserted properly before plugging in

the charger. Make sure that your battery is not completely discharged; if the battery power is empty for a long time, it may take around 20

Make sure charging is carried out under normal conditions (0°C to +40°C)

Make sure the SIM card has been correctly inserted

Make sure the service of your SIM card is available

· Make sure the chip on your SIM card is not damaged or

Make sure you have dialed a valid number and press the \_\_\_

Make sure your phone is connected to a network, and the

· For international calls, check the country and area codes

network is not overloaded or unavailable

#### My phone cannot connect to a network or "No service" is displayed Try connecting in another location

Unable to make outgoing calls

Verify the network coverage with your operator Check with your operator that your SIM card is valid Try selecting the available network(s) manually

Remove the battery and re-insert it, then restart the phone

Check the battery charge level

Check your subscription status with your operator (credit, SIM card valid, etc.) Make sure you have not barred outgoing calls

Make sure that your phone is not in flight mode

Invalid SIM card

User Data Format ALL user phone data: Contacts, messages

2014-1-3 18:16:33